






# 55D!%\$\$\$



Frekans	Hz	50
Jeneratör Modeli		55D!%\$\$\$
DY ]b': ]nÜh	TL	1400

## x N9 @@? @F

-  C < J ' A C H C F  
6U\_ia j Y\_j "Übia i'XU\U\_c`Um" gHb'gi dUd'i'a ctef
-  M5 '5@5FA =  
A ctef mÜ\_gin`\_U'Xi 'ibXU', U'i a Ugibi" b`YmYfY`\_a ctef  
\_cfi nÜb`U'Ufa`g]gY'a ]
-  5J F  
J c`HÜ'fb`&&\$`J j YmÜ", \$`J`fXU`gUV]hc`UFU`\_U'a Ugibi  
gU `ÜntÜb`c'cea UH\_j c`HÜ`fY[ `ÜH f
-  5 ifi`U\_ia ; Y\_]X] ]bXY`XYj fYmj`\_YgYfY`\_YbYfUk f`  
\_cfi nÜb` U'Yf
-  > ? @9 G GH9A  
`\_ ; U'i hifa UXUj YmÜ'gc i \_`Uj U'UFXU`\_c`Um, U'i hifa U  
Ua U, iznYb[ ]b`nÜ`ih`Ufi`ia`i`gU `ÜntÜb`g]gY'a

# 55D!%\$\$\$

## ● JENERATÖR

AC Nominal Güç	kW	0,85
Maksimum Güç	kW	0,95
57 'Bca ]bU'5_ia	57 'Bca ]bU'5_ia	3,90
87 'Bca ]bU'5_ia	57 'Bca ]bU'5_ia	6,00
Voltaj	V	230
Frekans	Hz	50
: Un'GUmigi		1
Güç Faktörü		0,80
MU_ihH' _Yfja ]	L/sa	0,66
G' fY_]uU' a U	Saat	5,00
Gürültü Seviyesi	dB(A)	64,00

## ● MOTOR

Devir	d/dk	3000
Silindir No.		1,0
Silindir Hacimi	mL.	55
MU_ihH' f'		Benzin
MU' ? UdUg]hYg]	L	0,4
MU_ihHUb_? UdUg]hYg]	L	2,1
GfUf'i Y_]		d']

## ● BOYUT

En	mm.	460
Boy	mm.	250
Yükseklik	mm.	400
5 ifi_	kg.	15,0