

AAP 5500E



Frekans	Hz	50
Jeneratör Modeli		AAP 5500E
DY]b:]nÜh	TL	3050

x N9 @@? @F



M5? #; x GH9F ; 9G
? U'Ub nÜ_ia]Üfibib[" nYba Yg]b]gU `UntÜb XYdc
" nYf]bXY_][" gHyfY



C < J 'A CHCF
6U_ia 'j Y_'i Übia i'XU\U'_cUm' gHyb'gi dUd'i'a cHcf



M5 '5@5FA =
A cHcf nÜ_gin'_U'Xi 'ibXU', U'i 'a Ugibi'" b'YnYfY_'a cHcfi
_cfi nÜb'U'Ufa 'g]gHy'a]



5J F
J c'Ü'Üb'&&\$'j 'j YnÜ", \$'j 'fXU'gU]hc'UfU'_U'a Ugibi
gU `UntÜb'cHca UH_j c'Ü^fY[" U'f'f



65? 'A G-N'5? y
? i fi 'Hd'za 'XU\U'Y'j Y'VU_ia '[YfY_Hfa YnYb'i ni b'" a 'f'
U_



H9? 9F @9? 'J 9'H5 'A 5'G GH9A
HU_ia UXU'_cUm'i_gU `UntÜb'& UXYhY_YfY_HYb'j Y'hi 'a U
_c'i bXÜb'c'i 'Ub'gYh



5 'ifi'_U_ia ; Y_]X]]bXY'XY'j fYmj'_YgYfY_'YbYfU'f'
_cfi nÜb' U'Yf



J C@HA 9HF 9
; fi d'" nYf]bXY'5"7"u'i_'j c'Ü'Üb'i[" gHyfYb'_UXfÜb



> ? @9'G GH9A
'_ ; U'i 'hfa UXU'j YnÜ'gc i_'\U'j U'UfXU'_cUm, U'i 'hfa U
Ua U, 'iznYb[]b'mÜ_Üf'i_ia i'gU `UntÜb'g]gHy'a



u : H'9@9A 5B@=< 5J 5: @HF 9G
9a]Yb'\U'j Ubib'hc'n'j Y'd]g]_YfXYb'Ufiba Ugibi'gU `UntÜb'
,]ZnY'Ya Ub'i'\U'j U'Z'Hyg]



6y My? 'M5? #H'5B? =
%!) 'hUfUgi'nÜ_ÜhÜb'_i

AAP 5500E

JENERATÖR

AC Nominal Güç	kW	4,00
	kVA	5,00
Maksimum Güç	kW	4,50
	kVA	5,50
57 'Bca]bU'5_ia	57 'Bca]bU'5_ia	17,30
Voltaj	V	230
Frekans	Hz	50
: Un'GUmigi		1
Güç Faktörü		0,80
MU_ihH' _Yfja]	L/sa	2,50
G' fy_]uU' a U	Saat	10,00
Gürültü Seviyesi	dB(A)	73,00

MOTOR

Devir	d/dk	3000
Güç	Hp	11,0
Silindir No.		1,0
Silindir Hacimi	mL.	337
MU_ihH' f'		Benzin
MU_? UdUg]fYg]	L	1,1
MU_ihHUb_? UdUg]fYg]	L	25,0
GRUfh Y_]		Elektrikli

BOYUT

En	mm.	540
Boy	mm.	680
Yükseklik	mm.	545
5 ifi_	kg.	83,0